

# Slimline Touchpad

The new Slimline Touchpad doesn't rest on its stylish curves alone, it controls every aspect of a modern security system, delivering an at-a-glance view of cameras, Z-Wave® automation devices, and every intrusion and environmental sensor. You can make the entire system instantly available in record time, delivered on a vivid 7" touchscreen.



## MOUNT UP, DOWN, OR ANYWHERE AROUND.

Slimline links to Connect+ and BAT-Connect Communicators with Wi-Fi® and includes a wall mount and a premium tabletop stand, giving you more flexibility. Direct-wired with battery backup, speedy installations are standard and bring the system in full view. The toughest choice may be what touchpad housing color best matches the décor.



#### MAKE OLD SYSTEMS NEW.

Pair Slimline with a BAT-Connect Communicator to quickly convert an old panel, and every sensor to a modern IoT platform. Slimline instantly upgrades or replaces a dusty old keypad with an integrated on-site control interface.

Four models and two colors are available with and without the Wi-Fi DeviceLink card for the Connect+ Hub.

RE667W (White) RE667B (Black)
RE667W-R (White with Wi-Fi DeviceLink Card)
RE667B-R (Black with Wi-Fi DeviceLink Card)





#### SLIMLINE TOUCHPAD SPEAKS.

Add audible zone status and Z-Wave device alerts to a security panel takeover, or perfect a new Connect+ Hub installation. Slimline Touchpad speaks changes to arming status, security and environmental sensors and Z-Wave™ devices.

## **SMARTER THAN** THE AVERAGE SMARTHOME.

Alula created the entire platform, merging security, video and automation to a single set of interactive controls. Just like the Alula App, the slimline touchpad controls every Z-Wave device. Smart locks, lights and thermostats are just a swipe and tap away.

Z-Wave notifications are lightning fast.

Khalil A., - Integrator Houson, TX













### **TECHNICAL SPECIFICATIONS**

RE667W (White) RE667W-R (White with Wi-Fi DeviceLink card) RE667B (Black) RE667B-R (Black with Wi-Fi DeviceLink card)

| Physical                      |   |
|-------------------------------|---|
| Dimensions in wall mount      | 4.27in [10.84cm] H x 7.42in [18.85cm] W x 1.60 [4.06cm] D |
| Dimensions in tabletop mount  | 3.60 [9.14cm] H x 7.42in [18.85cm] W x 4.58in [11.64cm] D |
| Weight                        | 20.64oz [585g]  |
| Pilot hole for screws         | Ø 1/8in [3mm]   |
| Pilot hole for wall anchors   | Ø 3/16in [4.7mm]  |
| Mounting fasteners            | #6 screws & 4 wall anchors (included)                     |
| Environmental                 |   |
| Operating temperature         | 32°F to 120°F (0°C to 49°C)                               |
| Maximum humidity              | 85% non-condensing relative humidity                      |
| Device Specifications         |   |
| Battery life                  | 4 hours   |
| Power transformer part number | RE012-6   |
| Input power                   | 100-240vac 50/60hZ 0.5A                                   |
| Output power                  | 12VDC, 1A   |
| Terminal block wire gauge     | 16-24 AWG   |
| Wireless range                | ~300 feet in open air                                     |
| Screen resolution             | 1024 x 600 pixels   |
| Screen size                   | 7 inches diagonally                                       |
| Accessories                   |   |
| Wi-Fi DeviceLink Card         | RE926RX (needed for Connect+ Base Hub only)               |
| Certification                 |   |
| RE667W, RE667B                | FCC, IC   |



Specifications subject to change without notice.



